# PRODUCT DATASHEET

# NiMH Battery Charger (CHUSB)

## **VERSATILE**

 Charges through the USB & wall outlet



# **Duo Charger**



### **FAST**

Charges
 2 AAA in 1.6 Hours
 (900 mAh)
 2 AA in 4.5 Hours
 (2500 mAh)



# **FUN**

 3 Fun colors available Green Blue Magenta



#### **Before Using Your Charger:**

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer NiMH batteries.

# **North American Region**

**Download Instructions and Warranty Information** 

English | Français | Español

### **Product Detail:**



**Designation:** Duo Charger

Color: Black and Green, Blue or Magenta
Capabilities: 1 to 2 "AA" NOTE: When charging a single

1 to 2 "AAA" battery, use bay (1) only

Charging Current: Quick Charge 1-2 "AA-AAA" 550mA

Slow Charge 1-2 "AA-AAA" 125mA

Trickle Charge: 20-60mA

Shutoff Mechanism: Delta V, Max Voltage and Timer Control

Delta V Detection 10mV per cell
Max Voltage 1.65V per cell

Max Timer Control Quick Charge "AA" 5.5 hours

Quick Charge "AAA" 1.5 hours Slow Charge "AA" No Timer Slow Charge "AAA" 10 hours

Charger Input: Quick Charge DC 5V 500mA

Slow Charge DC 5V 100mA

AC Adapter Input: 100-240V AC 50/60Hz 150mA

AC Adapter Output: DC 5V, 500mA
Weight (charger): 68 grams (2.4 oz.)
Dimensions (mm): 33 x 101 x 40 (H x L x W)
Safety Features: Delta V Charging Cut Off

Max Voltage Shutoff Reverse Polarity Protection Primary Battery Detection

#### **Important Notice**

This datasheet contains information specific to products manufactured at the time of its publication.

© Energizer Holdings, Inc.

Contents herein do not constitute a warranty.

